




























Fuse Accessory Selection Guide



Fuse Family	Size	PCB Fuse Clip	PCB Mount Holder	Panel Mount Holder	In-Line Fuse Holder	Fuse Block
 ABC AGC	1/4" x 1 1/4"	1Axxxx	HBH-I HBV-I	HTB HK HKP HMR HGA-C	HRK HFB HFA HHK HHN HFB	S-8000
 AGA	1/4" x 5/8"	1Axxxx	-	-	-	-
 AGW	1/4" x 7/8"	1Axxxx	-	-	HRK HFB	-
 AGX	1/4" x 1"	1Axxxx	-	HJL	HRK HFB	3828-1
 ATC	Auto Blade Fuse	1A5600 1A5780	-	-	HHF-JFCU	-
ATM	Auto Blade Fuse	1A5778 1A5779	-	-	HHM	-
 C519	5 mm x 15 mm	1Axxxx	-	-	HHT	-
C520	5 mm x 15 mm	1Axxxx	-	-	HHT	-
FNM FNQ	13/32" x 1 1/2"	1A3400	-	HPG	HEB	BMM603
FNQ-R KTK-R LP-CC	13/32" x 1 1/2"	1A3400	-	HPG	-	BCM603
FWH/5	1/4" x 1 1/4"	1Axxxx	HBH-I HBV-I	-	-	S-8000
GBA GLD	1/4" x 1 1/4"	1Axxxx	-	HLD HK	-	S-8000
 GBB	1/4" x 1 1/4"	1Axxxx	HBH-I HBV-I	HTB HK HKP HMR HGA-C	HRK HFB HFA HHK HHN HFB	S-8000
 GDA GDB GDC	5 mm x 20 mm	1Axxxx HTC-2xxM	H15 HBH-M HBV-M	HTB	HHT	HTC-15M HTC-60M
 GMA	5 mm x 20 mm	1Axxxx HTC-2xxM	H15 HBH-M HBV-M	HTB	HHT	HTC-15M HTC-60M
 GMC	5 mm x 20 mm	1Axxxx HTC-2xxM	H15 HBH-M HBV-M	HTB	HHT	HTC-15M HTC-60M
 GMD	5 mm x 20 mm	1Axxxx HTC-2xxM	H15 HBH-M HBV-M	HTB	HHT	HTC-15M HTC-60M

Fuse Family	Size	PCB Fuse Clip	PCB Mount Holder	Panel Mount Holder	In-Line Fuse Holder	Fuse Block
 KLM KTK	13/32" x 1 1/2"	1A3400	-	HPG	HEB	BMM603
 MDA MDL MDQ	1/4" x 1 1/4"	1Axxxx	HBH-I HBV-I	HTB HK HKP HMR HGA-C	HRK HFB HFA HHK HHN HFB	S-8000
 MDH	1/4" x 1 1/4"	1Axxxx	HBH-I HBV-I	HTB HK HKP HMR HGA-C	HRK HFB HFA HHK HHN HFB	S-8000
 PCTron	-	-	PCS	-	-	-
 S500 S501	5 mm x 20 mm	1Axxxx HTC-2xxM	H15 HBH-M HBV-M	HTB	HHT	HTC-15M HTC-60M
 S505 S506	5 mm x 20 mm	1Axxxx HTC-2xxM	H15 HBH-M HBV-M	HTB	HHT	HTC-15M HTC-60M
 SC-1 to 15A	13/32" x 1.31"	1A3400	-	HPS-EE	HEG	BG3011PQ
 SC-20A	13/32" x 1.41"	1A3400	-	HPS-JJ	HEH	BG3011PQ
 SC-25 to 30A	13/32" x 1.62"	1A3400	-	HPS-FF	HEC	BG3011PQ
 SC-35 to 60A	13/32" x 2 1/4"	1A3400	-	-	HEJ	G30060-1CR
 SFE	1/4" x various lengths (5/8" to 1 7/16")	1Axxxx	-	-	HR/HM	-
 SR-5 / SR-5F / SR-5H SS-5 / SS-5F / SR-5H	-	-	PCS	-	-	-
 TDC10/11	1/4" x 1 1/4"	1Axxxx	HBH-I HBV-I	HTB HK HKP HMR HGA-C	HRK HFB HFA HHK HHN HFB	S-8000
 TDC180 TDC600	1/4" x 1"	1Axxxx	-	HJL HJM	HRK HFB	3828-1
 TCP70	1/4" x 1"	1Axxxx	-	HJL HJM	HRK HFB	3828-1

Tools & resources

- [Webpage](#)
- [Parametric search tool](#)
- [How to select a fuse holder white paper](#)

Eaton
Electronics Division
1000 Eaton Boulevard
Cleveland, OH 44122
United States
www.eaton.com/electronics

© 2019 Eaton
All Rights Reserved
Printed in USA
Publication No. 10575 BU-MC16086
November 2019