

Fusedrawer for Fuse Links 5x20 mm resp. 6.3x32 mm

Standard or Medical Fuse drawer



Fuse drawer "Fingerrip" with voltage selector  
(Fuse links not enclosed)

Fuse drawer "Extrasafe" without voltage selector  
(Fuse links not enclosed)



### Description

- Component:  
Snap-in, Rear Mounting
- 2 Functions:  
Fuseholder for Fuse-links 5x20 mm or 6.3x32 mm, Voltage selector insert
- Approved together with power entry module

### Characteristics

- Fuse drawer meets requirements of medical standard IEC/EN 60601-1
- Suitable for use in equipment according to IEC/UL 60950

### Other versions on request

- Fuse drawer with other voltage values

### References

Fits to type: CD; CD-Bowdencable; KD; KD-Bowdencable; KEC; KFC

### Weblinks

[pdf-datasheet](#), [html-datasheet](#), [General Product Information](#), [Approvals](#), [CE declaration of conformity](#), [RoHS](#), [CHINA-RoHS](#), [REACH](#), [Mating Connectors](#), [e-Shop](#), [SCHURTER-Stock-Check](#), [Distributor-Stock-Check](#), [CAD-Drawings](#), [Accessories](#), [Detailed request for product](#)

### Voltage Selector Inserts

| Index | Marking on Voltage Selector Insert / Terminal No. |       |     |       |     |  |
|-------|---|-------|-----|-------|-----|--|
|       | KEC   | 1     | 2   | 3     | 4   |  |
| yy    | KD  | 3     | 4   | 5     | 6   |  |
| 00    |   | -     | -   | -     | -   |  |
| 01    |   | 100   | 120 | 220   | 240 |  |
| 02    |   | 110   | 150 | 220   | -   |  |
| 03    |   | 110   | -   | 220   | -   |  |
| 04    |   | 110   | 220 | 240   | -   |  |
| 05    |   | 115   | -   | 230   | -   |  |
| 06    |   | 117   | 220 | 240   | -   |  |
| 08    |   | 110 V | -   | 220 V | -   |  |
| 09    |   | 220   | -   | 240   | -   |  |
| 10    |   | 115   | 220 | 240   | -   |  |
| 11    |   | 110   | 120 | 220   | 240 |  |
| 12    |   | 115   | 230 | 240   | -   |  |
| 13    |   | 100   | 110 | 220   | 240 |  |
| 14    |   | 100   | 117 | 220   | 240 |  |
| 15    |   | 100   | 115 | 230   | -   |  |
| 16    |   | 100   | 120 | 230   | 240 |  |
| 17    |   | 115   | 120 | 230   | 240 |  |
| 18    |   | 115   | -   | 240   | -   |  |
| 19    |   | 220   | 120 | 240   | 230 |  |
| 20    |   | 100   | 120 | 230   | -   |  |
| 21    |   | 100   | -   | 220   | -   |  |
| 22    |   | 100   | 120 | 220   | 230 |  |
| 23    |   | 100   | 110 | 120   | -   |  |
| 24    |   | 200   | 220 | 240   | -   |  |
| 25    |   | 120   | -   | 230   | -   |  |
| 27    |   | 115   | 200 | 230   | -   |  |

| Index<br>yy | KEC<br>KD | Marking on Voltage Selector Insert / Terminal No. |     |     |     |
|-------------|-----------|---|-----|-----|-----|
|             |           | 1   | 2   | 3   | 4   |
|             |           | 3   | 4   | 5   | 6   |
| 28          |           | -   | 230 | 240 | -   |
| 29          |           | 100   | 117 | 125 | -   |
| 30          |           | 117   | 220 | 240 | 100 |
| 31          |           | 117   | 220 | 240 | 100 |
| 32          |           | 100   | 110 | 230 | 240 |
| 34          |           | 110   | 115 | 230 | 240 |
| 35          |           | 100   | 115 | 230 | 240 |
| 36          |           | 100   | 110 | 200 | 230 |
| 37          |           | 115   | 230 | 240 | 100 |
| 38          |           | 110   | 230 | 220 | 240 |
| 39          |           | 220   | 230 | 240 | -   |
| 40          |           | 100   | 110 | 127 | 230 |
| 42          |           | 100   | 115 | 120 | 230 |
| 43          |           | 911   | -   | 0E2 | -   |
| 44          |           | 100   | 115 | 127 | 230 |
| 45          |           | 100   | 115 | 230 | 127 |
| 46          |           | 100   | 120 | 200 | 230 |
| 48          |           | 100   | 120 | 208 | 230 |

Index "yy" matches the last two characters of the Order Number within the Variants

### All Variants

| Mounting   | Fuse-Link | Fuseholder | Comment                          | Order Number |
|------------|-----------|------------|----------------------------------|--------------|
| Fingergrip | 5 x 20    | 1-pole     | -                                | 4303.2114.yy |
| Extra-Safe | 5 x 20    | 1-pole     | -                                | 4303.2124.yy |
| Fingergrip | 5 x 20    | 1-pole     | -                                | 4303.2406    |
| Extra-Safe | 5 x 20    | 1-pole     | -                                | 4303.2408    |
| Fingergrip | 5 x 20    | 1-pole     | spare fuse case                  | 4303.2416    |
| Fingergrip | 5 x 20    | 2-pole     | -                                | 4303.2014.yy |
| Extra-Safe | 5 x 20    | 2-pole     | -                                | 4303.2024.yy |
| Fingergrip | 5 x 20    | 2-pole     | -                                | 4303.2401    |
| Extra-Safe | 5 x 20    | 2-pole     | -                                | 4303.2403    |
| Fingergrip | 5 x 20    | 2-pole     | shorting bar on the neutral side | 4303.2036.yy |
| Extra-Safe | 5 x 20    | 2-pole     | shorting bar on the neutral side | 4303.2037.yy |
| Fingergrip | 5 x 20    | 2-pole     | shorting bar on the neutral side | 4303.2411    |
| Extra-Safe | 5 x 20    | 2-pole     | shorting bar on the neutral side | 4303.2413    |
| Fingergrip | 6.3 x 32  | 1-pole     | -                                | 4303.2614.yy |
| Extra-Safe | 6.3 x 32  | 1-pole     | -                                | 4303.2624.yy |
| Fingergrip | 6.3 x 32  | 1-pole     | -                                | 4303.2906    |
| Extra-Safe | 6.3 x 32  | 1-pole     | -                                | 4303.2908    |
| Fingergrip | 6.3 x 32  | 2-pole     | -                                | 4303.2514.yy |
| Extra-Safe | 6.3 x 32  | 2-pole     | -                                | 4303.2524.yy |
| Fingergrip | 6.3 x 32  | 2-pole     | -                                | 4303.2901    |
| Extra-Safe | 6.3 x 32  | 2-pole     | -                                | 4303.2903    |
| Fingergrip | 6.3 x 32  | 2-pole     | shorting bar on the neutral side | 4303.2536.yy |
| Extra-Safe | 6.3 x 32  | 2-pole     | shorting bar on the neutral side | 4303.2537.yy |
| Fingergrip | 6.3 x 32  | 2-pole     | shorting bar on the neutral side | 4303.2911    |
| Extra-Safe | 6.3 x 32  | 2-pole     | shorting bar on the neutral side | 4303.2913    |

"yy" see Voltage Selector Inserts Table

**Packaging unit** 50 Pcs