



Electronics

a vital part of your world

Find Answers:

Saturday, 12 November, 2005

CATALOG

Cross Reference

- [Competitive Products](#)
- [Military Spec P/Ns](#)
- [Tyco Brand P/Ns](#)

- [Part Number Search](#)
- [Document Search](#)
- [Product Type Search](#)
- [Product Family Search](#)
- [Alphabetical Search](#)
- [RoHS/ELV Compliance & Alternates](#)
- [CAD Model Search](#)
- [Brand Search](#)
- [Tool Search](#)
- [Multiple Part Comparison](#)
- [Lead Free Solutions](#)
- [Help/Glossary](#)

[Home](#)

e-bulletin newsletter
SUBSCRIBE NOW!
 click here

M Series Pin & Socket Connectors

↳ M Series Connectors

AMP 200390-2 [Active](#)

[Not ELV or RoHS Compliant](#)

(Corporate P/N: 200390-2)

[Search for Compliant \(RoHS/ELV\)](#)

[Alternates](#)

[Search for Parts](#)

Document links for this part cannot be displayed. Your browser does not support inline frames or is currently configured not to display inline frames. Inline frames are supported in both Internet Explorer 5 and Netscape 6, as well as all later versions of these browsers.

| Related Part Information | | |
|---|--|---|
| General Information | eCommerce | Related Part Information |
| <ul style="list-style-type: none"> ✦ General Info ✦ Sales Info ✦ Assembly Subcontractors | <ul style="list-style-type: none"> ✦ Pricing & Availability | <ul style="list-style-type: none"> ✦ Tooling |

Photos & Line Drawings - The photographs and/or line drawings are representative images of a product for viewing purposes only.

[Product Photo](#)

| Searchable Features: | |
|--|------------------------------------|
| Brand: | AMP |
| RoHS/ELV Compliance: | Not ELV/RoHS compliant |
| Lead Free Solder Processes: | Not relevant for lead free process |
| Product Type: | Hardware |
| Hardware Type: | Guide Socket |
| Guide Socket Type: | Center |
| Mounting Hardware: | None |

| Other Properties: | |
|-------------------------------------|----------------------------|
| Lockwasher Material: | Stainless Steel |
| Hex Nut Material: | Steel |
| Packaging Method: | Loose Piece |
| Guide Socket [Pin] Material: | Stainless Steel |
| Guide Socket [Pin] Plating: | Passivated Stainless Steel |

Comment:

Used with 12 position high current connectors.
Used with 15, 16, and 42 position mixed connectors.
Used with 20 and 28 position high voltage connectors.
Used with 6, 14, 20, 26, 34, 41, 50, 75 and 104 position standard connectors.
Used with 6, 14, 20, 26, 34, 41, 50, 75 and 104 position posted connectors.

[Copyright](#) and [Privacy Statement](#)
Visit [Tyco International Ltd.](#)

[[Products](#) | [Catalog](#) | [Brands](#) | [Industries](#) | [Commerce](#) | [Supplier](#) | [Contact Us](#) | [About](#) | [Home](#)]